

### **FEATURES**

Low Power Loss, Hgih Efficiency

High Surge Capability

High Current Capability and Low Forward Voltage Drop







### **MECHANICAL DATA**

| Encapsulation: SOD-123FL Small Outline Plastic Package

| Polarity: Color Band Denotes Cathode end

| Mounting Position: Any

### **APPROVALS**

**RoHS** Compliance with 2011/65/EU

**HF** Compliance with IEC61249-2-21:2003

# MAXIMUM RATINGS ( $T_A = 25$ °C)

Parameter	Symbol	Value	Unit
Peak Repetitive Reverse Voltage @I <sub>R</sub> =1.0mA	$V_{RRM}$	40	V
Working Peak Reverse Voltage @I <sub>R</sub> =1.0mA	V <sub>RWM</sub>	40	V
DC Blocking Voltage @I <sub>R</sub> =1.0mA	$V_R$	40	V
RMS Reverse Voltage	$V_{R(RMS)}$	28	V
Average Rectified Output Current	I <sub>o</sub>	1	А
Non-Repetitive Peak Forward Surge Current 8.3ms single half sine-wave superimposed on rated load	I <sub>FSM</sub>	30	А
Power Dissipation (Note 1)	$P_{D}$	450	mW
Typical Thermal Resistance Junction to Ambi ent (Note 1)	R <sub>eJA</sub>	222	°C/W
Operating and Storage Temperature Range	$T_{J},T_{STG}$	-65 to +125	°C




# ELECTRICAL CHARACTERISTICS( $T_A = 25$ °C)


Parameter	Symbol	Test Conditions	Min.	Тур.	Max.	Unit
Reverse Breakdown Voltage (Note 2)	$V_{(BR)R}$	I <sub>R</sub> =1mA	40			V
Forward Voltage	V <sub>F</sub>	I <sub>F</sub> =1.0A			0.35	V
, and the second		I <sub>F</sub> =2.0A			0.40	
Reverse Leakage Current (Note 2)	I <sub>R</sub>	V <sub>R</sub> =40V,T <sub>A</sub> =25°C			220	μΑ
Neverse Leanuge earrein (Note 2)		V <sub>R</sub> =40V,T <sub>A</sub> =100°C		8.5		mA
Total capacitance	$C_{\scriptscriptstyleT}$	V <sub>R</sub> =4V, f=1MHz		50		pF

#### Notes:


- 1. FR-4 Board =  $70 \times 60 \times 1$ mm
- 2. Short duration pulse te st used to minmize self-heating effect.
- 3. Mounted on metal core PCBcitance


# **CHARACTERISTIC CURVES**


















### **SOLDERING PARAMETERS**

	Lead-free assembly		
	Temperature Max (T <sub>s(min)</sub> )	150°C	
Pre Heat	Temperature Max (T <sub>s(max)</sub> )	200°C	
	Time (min to max) $(t_s)$	60 – 180 secs	
Average ran	Average ramp up rate (Liquidus Temp $(T_L)$ to peak		
	T <sub>s(max)</sub> to T <sub>L</sub> - Ramp-up Rate		
Reflow	Temperature (T <sub>L</sub> ) (Liquidus)	217°C	
Kellow	Time (min to max) $(t_L)$	60 – 150 seconds	
Peak Temp	260°C		
Time within	20 – 40 seconds		
Ramp-dow	6°C/second max		
Time 25°C t	8 minutes max.		
Do not exce	260°C		




## **SOD-123FL PACKAGE INFORMATION**



	Ref.	MILLIII	mittineters inches	nes	
	Nel.	Min.	Max.	Min.	Max.
	А	0.95	1.45	0.037	0.057
	A1	0.00	0.10	0.000	0.004
	b	0.70	1.20	0.028	0.047
	С	0.05	0.30	0.002	0.012
	D	1.50	2.00	0.059	0.079
	Е	2.50	3.10	0.098	0.122
	L	0.35	0.90	0.014	0.035
	H <sub>E</sub>	3.40	3.90	0.134	0.154



### **RECOMMENDED PAD LAYOUT DIMENSIONS**



Ref.	Millimeters	Inches
А	4.20	0.165
В	1.50	0.059
С	1.20	0.047

### **ORDERING INFORMATION**

Part Number	Component Package	QTY/Reel	Reel Size
SS14DLF	SOD-123FL	3000PCS	7"



#### Headquarters

No.3387 Shendu Road Pujiang I&E Park Minhang Shanghai China 201000

# **Hotline** 400-021-5756

#### Web

Https://www.semiware.com

#### Sales Center

Tel: 86-21-3463-7458

Email: sales18@semiware.com

#### **Customer Service**

Tel: 86-21-5484-1001

Email: sales17@semiware.com

### **Technical Support**

Tel: 86-21-3463-7654

Email: fae01@semiware.com

### **Complaint & Suggestions**

Tel: 86-21-3463-7172

Ext: 8868

Email: cs03@semiware.com

#### By QR Code





Website

Machat

To find your local partner within Semiware's global website: www.semiware.com © 2022 Semiware Semiconductor Inc.

The content of this document has been carefully checked and understood. However, neither Semiware nor its subsidiaries assume any liability whatsoever for any errors or inaccuracies of this document and the consequences thereof. Published specifications are subject to change without notice. Product suitability for any area of application must ultimately be determined by the customer. In all cases, products must never be operated outside their published specifications. Semiware does not guarantee the availability of all published products. This disclaimer shall be governed by substantive Chinese law and resulting disputes shall be settled by the courts at the place of business of Semiware. Latest publications and a complete disclaimer can be downloaded from the Semiware website. All trademarks recognized.